

## SERVICE MODE(TBD)

Enter factory mode menu: press MENU + Numeric keys "1999" to enter factory mode.

FACTORY	
1.Brand	Sharp
2.Main-MCU Ver	SH_F6 V1.34...
3.Bootloader Ver	IDTV
4.Sub-MCU Ver	048
5.EEPROM Ver	010
6.Date	Apr 8 2010
7.Model name	SHARP_ATS...
8.Scalar	MT5387
9.Panel ID	136
10.Tuner ID	121

FACTORY	
34.UART_9600_...	YES
35.UART SW on ...	NO
36.RC Pass Thru	NO
37.CH Info to USB	>>
38.CEC Menu	>>
39.Clone to USB	>>
40.Clone from U...	>>
41.Reload HDMI ...	>>
42.Reset to Virgin	>>
43.Exit	>>